

(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 0 871 303 A2

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:

14.10.1998 Bulletin 1998/42(51) Int. Cl.⁶: **H04L 1/00, H04L 25/49**(21) Application number: **98106516.2**(22) Date of filing: **08.04.1998**

(84) Designated Contracting States:

**AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE**

Designated Extension States:

AL LT LV MK RO SI(30) Priority: **08.04.1997 US 43066 P**

(71) Applicants:

- **Demjanenko, Victor**
Pendleton, New York 14094 (US)

• **Hirzel, Frederic J.****Sunnyvale, California 94086 (US)**

(72) Inventors:

- **Demjanenko, Victor**
Pendleton, New York 14094 (US)
- **Hirzel, Frederic J.**
Sunnyvale, California 94086 (US)

(74) Representative: **Celestino, Marco**
ABM, Agenzia Brevetti & Marchi,
Via A. Della Spina 40
56125 Pisa (IT)

(54) Method for determining the attenuation of a PCM signal over a digital channel

(57) A method of determining digital channel attenuation; comprising the steps of: receiving a known training sequence of PCM codes, which PCM codes are subjected to the attenuation within the digital channel; quantizing the received known training sequence of PCM codes according to a predetermined thresholding procedure; identifying identical PCM codes created as a result of the thresholding procedure; and, determining the attenuation of the digital channel based upon the identification of identical PCM codes. A method is also disclosed for determining a digital channel PCM code transformation comprising receiving a known training sequence of PCM codes, which PCM codes are subjected to the PCM code transformation within the digital channel, quantizing the received known training sequence of PCM codes according to a predetermined thresholding procedure, and determining the transformation of transmitted codes to those received. A method is also disclosed for improved echo cancellation in a communications network having an analog and a digital modem, comprising saving codes transmitted from the digital modem to the analog modem for echo cancellation, transforming, by a mapping table, codes transmitted from said digital modem to codes received by the analog modem, and, using the received codes as a reference signal for cancellation of echo. A method of improved spectral shaping using a transmit shaping transfer function in a communications network having an analog and a digital modem, comprising, transforming, by a mapping table, codes transmitted from the digital modem to codes received by the analog modem,

using the received codes for transformation to their linear value equivalent representations, and, applying the linear value representations to the transmit shaping transfer function.

EP 0 871 303 A2

Description

Field of the Invention

This invention pertains generally to modem technology, more specifically to PCM modem technology, and more specifically, to a method for the discovery of the digital attenuation from a set of received PCM samples corresponding to a known set of transmit PCM samples.

Background of the Invention

This invention provides a method for the discovery of the digital attenuation from set of received pulse code modulation (PCM) samples corresponding to a known set of transmit PCM samples. The principal feature set used is the knowledge of which received PCM codes have become indistinguishable (i.e., are identical) as a result of the attenuation mapping. An alternative but equivalent feature set would be use of the absent received PCM codes.

The question of digital attenuation PAD mapping has been raised at recent meetings of the Telephone Industry of America (TIA) PCM Modem Ad-hoc Committee. Many participants have been hoping for a single industry standard mapping solution. We provide a solution, which will allow PCM modems to function properly throughout the entire telephone network including with private telephone equipment (PBX's and key systems).

TIA 464A

TIA 464A is the industry standard plan for private telephone equipment. Among other recommendations, this specification provides the recommended losses between T1 lines and other devices. If a PBX is designed according to the loss-plan specification as outlined in sections 4.8.4 and 4.8.5 of 464A, then it should not be necessary to attenuate the PCM on incoming T1 lines for on-premise (ONS) connections, since the recommended 3-dB loss is typically implemented in the analog circuitry of the ONS codec.

However, Inter-Tel's experience with customers using T1 lines suggests that the recommended 3-dB of insertion loss is inadequate and that T1 attenuation pads are indeed necessary. While the standard -3 and -6 dB pads are usually adequate, Inter-Tel has provided a wider-range of insertion loss as options for PBX customers. Inter-Tel has implemented digital gain control on its T1 line cards using two different methods:

- ROM-based mapping
- DSP-based algorithm

ROM Based Mapping

Inter-Tel first implemented attention pads via an EPROM circuit, which used the incoming PCM code as 8 bits of an address and additional address bits selecting the attenuation in 1 dB increments. The output of the EPROM was the attenuated digital PCM code. In this implementation, the attenuation range covered from 0 dB to -12 dB in 1 dB steps.

Experience with customers shows that 0 to -6 dB seems to be the most-often used range of T1 pad values. Taking into account the fixed 3-dB of loss included with our ONS card, the net insertion loss for to Digital CO connection is then -3dB to -9dB, which mimics well the typical net losses experienced by customers on ONS to Analog CO connections.

All attenuation tables in the EPROM preserved the LSB of the PCM to preserve the state of the Robbed Bit Signaling (RBS), if present. However, the preservation of the LSB is unnecessary if no RBS information passes through the ROM-based gain control circuitry.

The ROM-based look-up tables were generated by a custom C program using the following algorithm:

1. Expand incoming 8-bit, u-Law PCM to corresponding 14-bit, signed integer linear value, x
2. Calculate output, y, based on equation: $y = \text{INT} [x \cdot 10^{(\text{gain}/20)}] + 0.500$
3. Compress y back into its corresponding 8-bit u-Law value using G.711 decision values.

In addition to performing u-Law to u-Law digital gain control (DGC) through look-up tables, the EPROM also performs DGC through look-up tables for the following compression schemes:

- u-Law-to-A-law
- A-law-to-u-Law
- A-law-to-A-law

DSP Based Mapping

With the advent of DSP's, for their greater flexibility, the latest implementation uses the Analog Devices 21xx fixed point family of processors. The PCM codes are converted to/from linear values by the ADSP-21xx internal companding hardware. Inter-Tel's algorithm normalizes the linear value before applying the attenuation multiplier. The attenuation is selectable as a linear 1.15 fractional multiplier. The user interface selects the attenuation in fixed, 1-dB steps over a similar range as the previous implementation. The user configured dB attenuation is converted to the linear fractional multiplier by an algorithm. Moreover, the instructions in the Analog Devices DSP can use unbiased rounding, truncation and in newer family members, biased rounding. Inter-Tel's implementation uses the unbiased rounding option (RND) during the MAC instruction. This flexibility in rounding and truncation obviously can have a substantial effect on the actual attenuation mapping, with the additional caveat of having potentially different mappings for positive and negative PCM codes.

Detailed Description of the Preferred EmbodimentDetection of the Feature Set

After a receiver's equalizer has been trained, a known transmit sequence of PCM codes can be sent and received using either all or a useful subset of PCM codes. (This sequence may need to be sent multiple times to cover all 6 or 12 bit positions in a robbed bit signaling system.) The receiver can save the linear values for each received PCM code. From the known step size between adjacent PCM codes, the receiver can determine those PCM samples that it received which are indistinguishable. The indistinguishable samples arise from two transmit PCM codes which when scaled by the same attenuation and quantized according to a thresholding procedure create identical PCM codes.

An example taken from the attached attenuation table (pages A1-A2) which shows the attenuation for each uLaw PCM code when it is transformed by shifting from 1 to 26 codes numerically.

Example:

Transmitted		Received shifted by 1 PCM code			
uLaw	Linear	uLaw	Threshold	Attenuation	dB
129	7775	129	7647	0.983537	-0.14419
128	8031		7903	0.984062	-0.13955

Processing of Indistinguishable PCM Codes

The processing of the feature set relies on knowledge of the coding law (uLaw or Alaw) used. In practice, it is necessary to consider the preciseness of the numerics used in the attenuation process. Suggestions for accommodating implementation deviations is discussed in a later section. The attached C language source code provided as part of this application (pages B1- B21) implements a demonstration of the identification procedure indistinguishably codes. The basic algorithm is the following:

1. For each indistinguishable PCM code received, the original pair of transmitted PCM codes can be determined since the PCM codes are sent in a known training sequence. A set of indistinguishable transmitted PCM code pairs are determined from this training sequence.
2. For the first indistinguishable PCM code pair, determine the minimum attenuation required for the larger transmitted PCM code to be attenuated to a number of successive lower PCM codes. (A set of 30 successive lower PCM codes would be sufficient to cover an attenuation range of approximately 11 dB.) Then determine the maximum attenuation permitted for the smaller transmitted PCM code to be attenuated to the same successive lower PCM codes. (Minimum attenuation is numerically closer to one, i.e., a lesser attenuation, while a maximum attenuation is a greater attenuation.) If the maximum attenuation is a smaller attenuation than the minimum attenuation, discard the attenuation range as it represents a missing code rather than an indistinguishable code. The minimum and maximum attenuations for each successive lower PCM code forms an initial set of candidate attenuation ranges.
3. For each successive indistinguishable transmit PCM code pair, another set of possible attenuation ranges is determined using the procedure as described in Step 2. Each element of the candidate attenuation range set cre-

ated in Step 2 is searched for either full or partial overlap with any element of the possible attenuation range set. (In case of partial overlap, the attenuation range in the candidate set can be reduced for refined attenuation accuracy.) In case of no overlap, the candidate attenuation range should be discarded. The discard occurs because two different indistinguishable codes must arise from the same linear transformation.

4. Step 3 is repeated for successive pairs of indistinguishable transmit PCM code pairs until either a) the set of candidate attenuation ranges is reduced to a single range or b) all the pairs of indistinguishable transmit PCM code pairs have been processed.

In the first case, the actual attenuation is bounded by the single remaining attenuation range. We can say it is the detected attenuation can be the average of the high and low attenuations. Alternatively, if the history of each overlapping attenuation range is maintained (or regenerated) a probabilistic approach of determining a weighted median value for determining the detected attenuation can be implemented.

For the second case where the attenuation appears to remain non-unique, the set of candidate attenuation ranges can be used to determine multiple sets of indistinguishable PCM code pairs can be determined for each candidate attenuation. The generated sets of indistinguishable PCM code pairs can then be matched with the original received set. The generated set using the correct attenuation should match nearly identically if not identically. The sets corresponding to incorrect potential attenuations would generate significant number of additional pairs of indistinguishable PCM code pairs or have missing indistinguishable PCM code pairs. Thus the correct detected attenuation can still be determined using this procedure. (Multiple candidate attenuations appear to arise from attenuations of 6 dB or greater combined with the decreasing step sizes used in with uLaw or Alaw companding.)

Processing of Missing PCM Codes

The procedure described above for using indistinguishable PCM codes to determine the attenuation can be adapted to operate with missing received PCM codes. The transmitted PCM codes corresponding each of the received PCM codes around the missing PCM code can be determined. Follow the same algorithm except that the minimum and maximum attenuations are exchanged in the algorithms. In other words, the larger transmitted PCM code produces the maximum attenuation and the smaller transmitted PCM code produces the minimum attenuation. With this adaptation, the algorithm described remains essentially the same.

Example:

Transmitted		Received shifted by 1 PCM code			
uLaw	Linear	uLaw	Threshold	Attenuation	dB
144	3999	144	3935	0.983996	-0.14013
143	4191		4063	0.969458	-0.26942

Other Variations

For robustness with real signals corrupted by noise, it may be desirable to allow a certain number of pairs of indistinguishable PCM codes not to match a candidate range. An alternative to simply dropping a candidate attenuation range would be to use a probabilistic greatest likelihood model for selection of the detected attenuation.

Furthermore, given that implementers of digital attenuation pads may understand and implement the mapping process slightly differently (i.e., use of G.711 threshold values or average between PCM codes) and allow various inaccuracies in the numerical operations (numeric representation, rounding, truncation, etc.), each candidate attenuation range may need to be broadened to make overlap again more likely. The broadening can be by a fixed value or a relative amount about the attenuation computed. The previous suggestion of discarding a certain number of pairs of indistinguishable PCM codes also addresses this problem as very few pairs are likely to be affected by these numerical inaccuracies.

As for digital attenuation pads that pass through the robbed bit signaling (RBS) information, the algorithms presented can also be applied except that the indistinguishable transmit PCM code pairs will be separated by one code and a second indistinguishable transmit PCM code pair will be adjacent. The candidate attenuation ranges become bigger, but still can be matched by the procedures presented in this invention.

The procedures described in this invention suggest a robust manner to identify the digital channel attenuation

though the use of received PCM codes corresponding to a known transmit PCM code sequence. The use of such an algorithm would be necessary when the FCC permits the channel power to be increased in compensation for the systematic digital attenuations.

We further suggest that knowledge of the exact received PCM code set may be preferred by both the analog and digital PCM modems. Echo cancellation in the digital PCM modem may operate with incrementally better performance with the knowledge of actual PCM codes presented to the Codec. The receiver's desired spectral shaping can be more precisely honored by having the transmitter use the knowledge of the actual PCM codes presented to the Codec in the shaping function implementation, then reversely mapping the PCM code after shaping to the transmit PCM code to be sent.

The exclusive use of pre-identified attenuation table mappings would make the PCM modem technology incapable of operating with existing private telephone equipment. It is recommended that the attenuation pad mappings be discovered for each connection.

Claims

1. A method of determining digital channel attenuation, comprising:

receiving a known training sequence of PCM codes, which PCM codes are subjected to said attenuation within said digital channel;
quantizing said received known training sequence of PCM codes according to a predetermined thresholding procedure;
identifying identical PCM codes created as a result of said thresholding procedure; and,
determining said attenuation of the digital channel based upon said identification of identical PCM codes.

2. A method of determining digital channel attenuation, comprising:

receiving a known training sequence of PCM codes, which PCM codes are subjected to said attenuation within said digital channel;
quantizing said received known training sequence of PCM codes according to a predetermined thresholding procedure;
identifying PCM codes omitted as a result of said thresholding procedure; and,
determining said attenuation of the digital channel based upon said identification of omitted PCM codes.

3. A method of determining a digital channel PCM code transformation comprising:

receiving a known training sequence of PCM codes, which PCM codes are subjected to said PCM code transformation within said digital channel;
quantizing said received known training sequence of PCM codes according to a predetermined thresholding procedure; and
determining the transformation of transmitted codes to those received.

4. A method of improved echo cancellation in a communication network having an analog and a digital modem, comprising:

saving codes transmitted from said digital modem to said analog modem for echo cancellation;
transforming, by a mapping table, codes transmitted from said digital modem to codes received by said analog modem; and
using said received codes as a reference signal for cancellation of echo.

5. A method of improved spectral shaping using a transmit shaping transfer function in a communications network having an analog and a digital modem, comprising:

transforming, by a mapping table, codes transmitted from said digital modem to codes received by said analog modem;
using said received codes for transformation to their linear value equivalent representations; and,
applying said linear value representations to said transmit shaping transfer function.

ULaw Linear	by 1	by 2	by 3	by 4	by 5	by 6	by 7	by 8	by 9	by 10	by 11	by 12	by 13	by 14	by 15	by 16	by 17	by 18	by 19	by 20	by 21	by 22	by 23	by 24	by 25	by 26
-------------	------	------	------	------	------	------	------	------	------	-------	-------	-------	-------	-------	-------	-------	-------	-------	-------	-------	-------	-------	-------	-------	-------	-------

A1

→ Creates a missing PCM code in the sequence received
← Creates a pair of indistinguishable PCM codes

A1

255	0	-6.0206	-12.0412	15.583	22.9226	21.5836	12.0412	21.5836	22.9226	15.583	-12.0412	-6.0206	0
254	4	-0.0877	-4.2056	15.583	22.9226	21.5836	12.0412	21.5836	22.9226	15.583	-12.0412	-4.2056	4
253	8	-0.1984	-4.0324	-5.9937	-9.0519	-11.251	-16.43	-9.0519	-11.251	-16.43	-5.9937	-4.0324	8
252	12	-0.5077	-2.8977	-9.8956	-16.0256	-20.4514	-24.0024	-16.0256	-20.4514	-24.0024	-9.8956	-2.8977	12
251	16	-0.9459	-2.0047	-5.9357	-9.8956	-16.0256	-20.4514	-9.8956	-16.0256	-20.4514	-5.9357	-2.0047	16
250	20	-1.5115	-1.0884	-4.0324	-5.9937	-9.0519	-11.251	-5.9937	-9.0519	-11.251	-4.0324	-1.0884	20
249	24	-2.2477	-0.8077	-2.8977	-9.8956	-16.0256	-20.4514	-9.8956	-16.0256	-20.4514	-2.8977	-0.8077	24
248	28	-3.1857	-0.5077	-2.0047	-5.9357	-9.8956	-16.0256	-5.9357	-9.8956	-16.0256	-2.0047	-0.5077	28
247	32	-4.3236	-0.1984	-1.5115	-1.0884	-4.0324	-5.9937	-1.0884	-4.0324	-5.9937	-1.5115	-0.1984	32
246	36	-5.6657	0.1415	-1.2732	-0.9459	-3.1857	-5.6657	-0.9459	-3.1857	-5.6657	-1.2732	0.1415	36
245	40	-7.2124	0.4841	-0.8077	-2.8977	-9.8956	-16.0256	-2.8977	-9.8956	-16.0256	-0.8077	0.4841	40
244	44	-8.9697	1.0884	-0.5077	-2.0047	-5.9357	-9.8956	-5.9357	-9.8956	-9.8956	-0.5077	1.0884	44
243	48	-10.9457	1.5115	-0.1984	-1.5115	-1.0884	-4.0324	-4.0324	-1.0884	-4.0324	-1.5115	1.5115	48
242	52	-13.1361	1.984	0.1415	-1.2732	-0.9459	-3.1857	-3.1857	-0.9459	-3.1857	0.1415	1.984	52
241	56	-15.5397	2.4024	0.4841	-0.8077	-2.8977	-9.8956	-9.8956	-2.8977	-9.8956	0.4841	2.4024	56
240	60	-18.1541	2.8977	0.8077	-2.0047	-5.9357	-9.8956	-9.8956	-5.9357	-9.8956	0.8077	2.8977	60
239	64	-20.9807	3.3680	1.0884	-0.5077	-2.0047	-5.9357	-5.9357	-0.5077	-5.9357	1.0884	3.3680	64
238	68	-23.9197	3.8125	1.5115	-0.1984	-1.5115	-1.0884	-1.0884	-0.1984	-1.5115	1.5115	3.8125	68
237	72	-26.9712	4.2361	1.984	0.1415	-1.2732	-0.9459	-0.9459	-1.2732	-0.9459	1.984	4.2361	72
236	76	-30.1353	4.6432	2.4024	0.4841	-0.8077	-2.8977	-2.8977	-0.8077	-2.8977	2.4024	4.6432	76
235	80	-33.4129	5.0357	2.8977	0.8077	-2.0047	-5.9357	-5.9357	-2.0047	-5.9357	2.8977	5.0357	80
234	84	-36.8041	5.4125	3.3680	1.0884	-0.5077	-2.0047	-2.0047	-0.5077	-2.0047	3.3680	5.4125	84
233	88	-40.3097	5.7736	3.8125	1.5115	-0.1984	-1.5115	-1.5115	-0.1984	-1.5115	3.8125	5.7736	88
232	92	-43.9307	6.1191	4.2361	1.984	0.1415	-1.2732	-1.2732	0.1415	-1.2732	4.2361	6.1191	92
231	96	-47.6671	6.4493	4.6432	2.4024	0.4841	-0.8077	-0.8077	0.4841	-0.8077	4.6432	6.4493	96
230	100	-51.5197	6.7643	5.0357	2.8977	0.8077	-2.0047	-2.0047	0.8077	-2.0047	5.0357	6.7643	100
229	0	-55.4761	7.0792	5.4125	3.3680	1.0884	-0.5077	-0.5077	1.0884	-0.5077	5.4125	7.0792	0
228	4	-59.5497	7.3783	5.7736	3.8125	1.5115	-0.1984	-0.1984	1.5115	-0.1984	5.7736	7.3783	4
227	8	-63.7397	7.6729	6.1191	4.2361	1.984	0.1415	-1.2732	0.1415	-1.2732	6.1191	7.6729	8
226	12	-68.0457	7.9632	6.4493	4.6432	2.4024	0.4841	-0.8077	-0.8077	0.4841	4.6432	7.9632	12
225	16	-72.4777	8.2493	6.7643	5.0357	2.8977	0.8077	-2.0047	-2.0047	0.8077	5.0357	8.2493	16
224	20	-77.0357	8.5312	7.0792	5.4125	3.3680	1.0884	-0.5077	-0.5077	1.0884	5.4125	7.0792	20
223	24	-81.7197	8.8089	7.3783	5.7736	3.8125	1.5115	-0.1984	-0.1984	1.5115	5.7736	7.3783	24
222	28	-86.5297	8.5312	7.0792	5.4125	3.3680	1.0884	-0.5077	-0.5077	1.0884	5.4125	7.0792	28
221	32	-91.4657	8.2493	6.7643	5.0357	2.8977	0.8077	-2.0047	-2.0047	0.8077	5.0357	8.2493	32
220	36	-96.5297	7.9632	6.4493	4.6432	2.4024	0.4841	-0.8077	-0.8077	0.4841	4.6432	7.9632	36
219	40	-101.7197	7.6729	6.1191	4.2361	1.984	0.1415	-1.2732	0.1415	-1.2732	6.1191	7.6729	40
218	44	-107.0357	7.3783	5.7736	3.8125	1.5115	-0.1984	-0.1984	1.5115	-0.1984	5.7736	7.3783	44
217	48	-112.4777	7.0792	5.4125	3.3680	1.0884	-0.5077	-0.5077	1.0884	-0.5077	5.4125	7.0792	48
216	52	-118.0397	6.7643	5.0357	2.8977	0.8077	-2.0047	-2.0047	0.8077	-2.0047	5.0357	6.7643	52
215	56	-123.7197	6.4493	4.6432	2.4024	0.4841	-0.8077	-0.8077	0.4841	-0.8077	4.6432	6.4493	56
214	60	-129.5197	6.1191	4.2361	1.984	0.1415	-1.2732	-1.2732	0.1415	-1.2732	4.2361	6.1191	60
213	64	-135.4397	5.7736	3.8125	1.5115	-0.1984	-0.1984	1.5115	-0.1984	1.5115	3.8125	5.7736	64
212	68	-141.4797	5.4125	3.3680	1.0884	-0.5077	-0.5077	1.0884	-0.5077	1.0884	3.3680	5.4125	68
211	72	-147.6397	5.0357	2.8977	0.8077	-2.0047	-2.0047	0.8077	-2.0047	0.8077	2.8977	5.0357	72
210	76	-153.9197	4.6432	2.4024	0.4841	-0.8077	-0.8077	0.4841	-0.8077	0.4841	2.4024	4.6432	76
209	80	-160.3197	4.2361	1.984	0.1415	-1.2732	-1.2732	0.1415	-1.2732	0.1415	1.984	4.2361	80
208	84	-166.8397	3.8125	1.5115	-0.1984	-0.1984	1.5115	-0.1984	1.5115	-0.1984	1.5115	3.8125	84
207	88	-173.4797	3.3680	1.0884	-0.5077	-0.5077	1.0884	-0.5077	1.0884	-0.5077	1.0884	3.3680	88
206	92	-180.2397	2.8977	0.8077	-2.0047	-2.0047	0.8077	-2.0047	0.8077	-2.0047	0.8077	2.8977	92
205	96	-187.1197	2.4024	0.4841	-0.8077	-0.8077	0.4841	-0.8077	0.4841	-0.8077	0.4841	2.4024	96
204	100	-194.1197	1.984	0.1415	-1.2732	-1.2732	0.1415	-1.2732	0.1415	-1.2732	0.1415	1.984	100
203	0	-201.2397	1.5115	-0.1984	-0.1984	1.5115	-0.1984	1.5115	-0.1984	1.5115	-0.1984	1.5115	0
202	4	-208.4797	1.0884	-0.5077	-0.5077	1.0884	-0.5077	1.0884	-0.5077	1.0884	-0.5077	1.0884	4
201	8	-215.8397	0.5077	-2.0047	-2.0047	0.8077	-2.0047	0.8077	-2.0047	0.8077	-2.0047	0.5077	8
200	12	-223.3197	0.0877	-2.8977	-2.8977	0.8077	-2.8977	0.8077	-2.8977	0.8077	-2.8977	0.0877	12
199	16	-230.9197	-0.3125	-3.8125	-3.8125	1.5115	-3.8125	1.5115	-3.8125	1.5115	-3.8125	-0.3125	16
198	20	-238.6397	-0.7125	-4.8125	-4.8125	2.4024	-4.8125	2.4024	-4.8125	2.4024	-4.8125	-0.7125	20
197	24	-246.4797	-1.1125	-5.8125	-5.8125	3.3680	-5.8125	3.3680	-5.8125	3.3680	-5.8125	-1.1125	24
196	28	-254.4397	-1.5125	-6.8125	-6.8125	4.3236	-6.8125	4.3236	-6.8125	4.3236	-6.8125	-1.5125	28
195	32	-262.5197	-1.9125	-7.8125	-7.8125	5.3680	-7.8125	5.3680	-7.8125	5.3680	-7.8125	-1.9125	32
194	36	-270.7197	-2.3125	-8.8125	-8.8125	6.4493	-8.8125	6.4493	-8.8125	6.4493	-8.8125	-2.3125	36
193	40	-279.0397	-2.7125	-9.8125	-9.8125	7.5832	-9.8125	7.5832	-9.8125	7.5832	-9.8125	-2.7125	40
192	44	-287.4797	-3.1125	-10.8125	-10.8125	8.7643	-10.8125	8.7643	-10.8125	8.7643	-10.8125	-3.1125	44
191	48	-296.0397	-3.5125	-11.8125	-11.8125	9.9937	-11.8125	9.9937	-11.8125	9.9937	-11.8125	-3.5125	48
190	52	-304.7197	-3.9125	-12.8125	-12.8125	11.2736	-12.8125	11.2736	-12.8125	11.2736	-12.8125	-3.9125	52
189	56	-313.5197	-4.3125	-13.8125	-13.8125	12.6043	-13.8125	12.6043	-13.8125	12.6043	-13.8125	-4.3125	56
188	60	-322.4397	-4.7125	-14.8125	-14.8125	13.9857	-14.8125	13.9857	-14.8125	13.9857	-14.8125	-4.7125	60
187	64	-331.4797	-5.1125	-15.8125	-15.8125	15.4125	-15.8125	15.4125	-15.8125	15.4125	-15.8125	-5.1125	64
186	68	-340.6397	-5.5125	-16.8125	-16.8125	16.8857	-16.8125	16.8857	-16.8125	16.8857	-16.8125	-5.5125	68
185	72	-350.0397	-5.9125	-17.8125	-17.8125	18.4043	-17.8125	18.4043	-17.8125	18.4043	-17.8125	-5.9125	72
184	76	-359.5797	-6.3125	-18.8125	-18.8125	19.9643	-18.8125	19.9643	-18.8125	19.9643	-18.8125	-6.3125	76
183	80	-369.2397	-6.7125	-19.8125	-19.8125	21.5643	-19.8125	21.5643	-19.8125	21.5643	-19.8125	-6.7125	80
182	84	-379.0397	-7.1125	-20.8125	-20.8125	23.2043	-20.8125	23.2043	-20.8125	23.2043	-20.8125	-7.1125	84
181	88	-388.9797	-7.5125	-21.8125	-21.8125	24.8857	-21.8125	24.8857	-21.8125	24.8857	-21.8125	-7.5125	88
180	92	-399.0397	-7.9125	-22.8125	-22.8125	26.6043	-22.8125	26.6043	-22.8125	26.6043	-22.8125	-7.9125	92
179	96	-409.2397	-8.3125	-23.8125	-23.8125	28.3643	-23.8125	28.3643	-23.8125	28.3643	-23.8125	-8.3125	96
178	100	-419.5797	-8.7125	-24.8125	-24.8125	30.1643	-24.8125	30.1643	-24.8125	30.1643	-24.8125	-8.7125	100
177	0	-430.0397	-9.1125	-25.8125	-25.8125	32.0043	-25.8125	32.0043	-25.8125	32.0043	-25.8125	-9.1125	0
176	4	-440.6397	-9.5125	-26.8125	-26.8125	33.8857	-26.8125	33.8857	-26.8125	33.8857	-26.8125	-9.5125	4
175	8	-451.3797	-9.9125	-27.8125	-27.8125	35.8043	-27.8125	35.8043	-27.8125	35.8043	-27.8125	-9.9125	8
174	12	-462.2397	-10.3125	-28.8125	-28.8125	37.7643	-28.8125	37.7643	-28.8125				

181	495	-0.28539	0.56048	-0.86595	-1.20236	1.53114	1.87265	-2.26281	-2.59876	-3.19121	-3.81639	-4.76035	-4.73447	-5.27252	-5.76131	6.23415	6.82501	7.20333	7.67127	7.91594	8.27144	8.63208	8.93134	9.43777	9.86416	10.1126
190	527	-0.26779	-0.8795	-1.24539	-1.43006	1.74667	2.17624	-2.16175	-2.77224	-3.42799	-3.93532	-4.3604	-4.80736	-5.27252	-5.76131	6.23415	6.82501	7.20333	7.67127	7.91594	8.27144	8.63208	8.93134	9.43777	9.86416	10.1126
199	559	-0.25274	-0.77882	-1.34153	-1.63662	1.94209	2.36569	-2.50227	-3.02124	-3.64541	-4.04209	-4.44734	-4.87242	-5.31938	-5.78029	6.25685	6.81742	7.30281	7.80284	8.29642	8.78456	9.26788	9.74693	10.22157	10.6931	10.9883
208	591	-0.23819	-0.73575	-1.26331	-1.83504	2.12011	2.42166	-2.74247	-3.26124	-3.84123	-4.38431	-4.90044	-5.38964	-5.85029	-6.29138	6.75285	7.23824	7.70081	8.15084	8.58842	9.01599	9.43367	9.84134	10.23901	10.6267	10.9711
217	623	-0.22549	-0.66644	-1.19376	-1.72134	2.23305	2.53141	-2.83161	-3.35022	-3.92127	-4.45431	-4.95044	-5.41964	-5.86029	-6.28138	6.74285	7.22824	7.68081	8.11784	8.53942	8.94599	9.33767	9.71434	10.08601	10.4427	10.7741
226	655	-0.21449	-0.61601	-1.13147	-1.72134	2.23305	2.53141	-2.83161	-3.35022	-3.92127	-4.45431	-4.95044	-5.41964	-5.86029	-6.28138	6.74285	7.22824	7.68081	8.11784	8.53942	8.94599	9.33767	9.71434	10.08601	10.4427	10.7741
235	687	-0.20468	-0.56912	-1.07636	-1.54578	2.04314	2.37027	-2.73242	-3.24751	-3.76124	-4.25431	-4.71964	-5.15964	-5.57029	-5.96138	6.41285	6.89824	7.35081	7.78784	8.20942	8.61599	9.00767	9.38434	9.74601	10.0927	10.4241
244	719	-0.19547	-0.52389	-1.02456	-1.47078	1.94492	2.31144	-2.63556	-3.15022	-3.66124	-4.14731	-4.60044	-5.02964	-5.43029	-5.81138	6.25285	6.71824	7.15081	7.56084	7.94842	8.31599	8.67367	9.02134	9.35901	9.6867	10.0041
253	751	-0.18703	-0.47989	-0.97285	-1.40778	1.84902	2.21554	-2.51964	-3.03431	-3.54531	-4.03244	-4.48554	-4.90614	-5.29729	-5.66838	6.10985	6.57524	6.99781	7.38784	7.75542	8.10309	8.44076	8.76843	9.08610	9.39377	9.69144
262	783	-0.17933	-0.43289	-0.92081	-1.34078	1.75252	2.11904	-2.42316	-2.93784	-3.44884	-3.93591	-4.38904	-4.80964	-5.19029	-5.55138	6.00135	6.46674	6.88931	7.27934	7.64692	8.00459	8.35226	8.69093	9.01860	9.33627	9.64394
271	815	-0.17222	-0.38744	-0.86941	-1.28405	1.65887	2.02539	-2.32951	-2.84424	-3.35524	-3.84231	-4.29544	-4.71604	-5.10719	-5.47829	5.82985	6.29524	6.71781	7.10784	7.46542	7.80309	8.13076	8.44843	8.75610	9.05377	9.34144
280	847	-0.16565	-0.34284	-0.81641	-1.23192	1.56385	1.93047	-2.23459	-2.74924	-3.26024	-3.74731	-4.19044	-4.60104	-4.97219	-5.31329	5.72485	6.19024	6.60281	6.97284	7.31042	7.62809	7.94576	8.25343	8.55110	8.83877	9.11644
289	879	-0.15955	-0.29876	-0.76541	-1.17987	1.46883	1.83545	-2.12951	-2.64424	-3.15524	-3.64231	-4.08544	-4.49604	-4.86719	-5.20829	5.61985	6.08524	6.49781	6.86984	7.20742	7.52509	7.84276	8.15043	8.44810	8.73577	9.01344
298	911	-0.15395	-0.25376	-0.71641	-1.13143	1.37381	1.74043	-2.03151	-2.54624	-3.05724	-3.54431	-3.98744	-4.39804	-4.76919	-5.10029	5.51185	5.97724	6.39081	6.76284	7.09042	7.40809	7.71576	8.01343	8.30110	8.58877	8.86644
307	943	-0.14884	-0.21376	-0.66741	-1.08291	1.27879	1.64541	-1.93651	-2.45124	-2.96224	-3.44931	-3.89244	-4.29304	-4.65419	-4.98529	5.39685	5.86224	6.27581	6.64784	6.97542	7.28309	7.58076	7.86843	8.14610	8.41377	8.68144
316	975	-0.14424	-0.16864	-0.61841	-1.03437	1.18377	1.55039	-1.84151	-2.35624	-2.86724	-3.35431	-3.80744	-4.21804	-4.58919	-4.92029	5.33185	5.79724	6.21081	6.58284	6.91042	7.21809	7.51576	7.80343	8.08110	8.34877	8.61644
325	1007	-0.13964	-0.12304	-0.56941	-0.98583	1.08879	1.45541	-1.74651	-2.26124	-2.77224	-3.25931	-3.71244	-4.12304	-4.49419	-4.82529	5.23685	5.70224	6.11581	6.48784	6.81542	7.12309	7.42076	7.70843	7.98610	8.26377	8.54144
334	1039	-0.13504	-0.07644	-0.52081	-0.93726	0.99377	1.36039	-1.65151	-2.16624	-2.67724	-3.16431	-3.61744	-4.02804	-4.39919	-4.73029	5.14185	5.60724	6.02081	6.39284	6.72042	7.02809	7.32576	7.61343	7.89110	8.16877	8.44644
343	1071	-0.13044	-0.02984	-0.47221	-0.88867	0.90022	1.26684	-1.55791	-2.07264	-2.58364	-3.07071	-3.52384	-3.93444	-4.30559	-4.63669	5.05341	5.51884	5.93241	6.30444	6.63202	6.93969	7.23736	7.52503	7.80270	8.08037	8.35804
352	1103	-0.12584	-0.01424	-0.42361	-0.84010	0.80167	1.16829	-1.45939	-1.97504	-2.48604	-2.99704	-3.48411	-3.93724	-4.34784	-4.71899	5.00495	5.47034	5.88391	6.25594	6.58352	6.88119	7.16886	7.44653	7.72420	8.00187	8.27954
361	1135	-0.12124	0.00034	-0.37401	-0.79153	0.70314	1.06976	-1.36086	-1.87651	-2.38751	-2.89851	-3.38564	-3.84874	-4.27934	-4.65049	4.91605	5.38144	5.79501	6.16704	6.49462	6.80229	7.09996	7.38763	7.67530	7.96297	8.25064
370	1167	-0.11664	0.01074	-0.32441	-0.74302	0.60467	1.07129	-1.30239	-1.81804	-2.32904	-2.84004	-3.32711	-3.78024	-4.21084	-4.58199	4.84755	5.31294	5.72651	6.10854	6.43612	6.73379	7.02146	7.30913	7.59680	7.88447	8.17214
379	1199	-0.11204	0.02114	-0.27481	-0.69445	0.50622	1.07281	-1.24391	-1.75956	-2.27056	-2.78156	-3.27864	-3.74174	-4.17234	-4.54349	4.79905	5.26444	5.67801	6.06004	6.39762	6.70529	7.00296	7.29063	7.57830	7.86597	8.15364
388	1231	-0.10744	0.03124	-0.22561	-0.64586	0.40779	1.07433	-1.17651	-1.69216	-2.20316	-2.71416	-3.21124	-3.67434	-4.10494	-4.47609	4.73165	5.19704	5.61061	6.00264	6.34022	6.64789	6.94556	7.23323	7.52090	7.80857	8.09624
397	1263	-0.10284	0.04134	-0.17599	-0.59728	0.30860	1.07585	-1.12803	-1.64368	-2.15468	-2.66568	-3.16274	-3.62584	-4.05644	-4.42759	4.68315	5.14854	5.56211	5.95414	6.32572	6.63339	6.92106	7.20873	7.49640	7.78407	8.07174
406	1295	-0.10124	0.05144	-0.12619	-0.54869	0.20951	1.07737	-1.08003	-1.59568	-2.10668	-2.61768	-3.11474	-3.57784	-4.00844	-4.37959	4.63875	5.10414	5.51771	5.90974	6.28132	6.58899	6.87666	7.16433	7.45200	7.73967	8.02734
415	1327	-0.10164	0.06154	-0.07641	-0.49910	0.11032	1.07889	-1.03121	-1.54686	-2.05786	-2.56886	-3.07004	-3.52314	-3.95374	-4.32489	4.59335	5.05874	5.47231	5.86434	6.24592	6.55359	6.84126	7.12893	7.41660	7.70427	7.99194
424	1359	-0.10204	0.07164	-0.02621	-0.44951	0.01103	1.08041	-1.00003	-1.50746	-2.01846	-2.52946	-3.03064	-3.48374	-3.89434	-4.26549	4.55195	5.01734	5.43091	5.82294	6.20452	6.51219	6.79986	7.08753	7.37520	7.66287	7.95054
433	1391	-0.10244	0.08174	-0.01631	-0.39992	0.09164	1.08193	-0.95003	-1.45806	-1.96906	-2.48006	-2.98124	-3.43434	-3.84494	-4.21609	4.50045	4.96584	5.37941	5.77144	6.15302	6.46069	6.74836	7.03603	7.32370	7.61137	7.89904
442	1423	-0.10284	0.09184	-0.00641	-0.35033	0.19275	1.08345	-0.90013	-1.40868	-1.91968	-2.43068	-2.93186	-3.38494	-3.79554	-4.16669	4.48495	4.95034	5.36391	5.75594	6.13752	6.44519	6.73286	7.02053	7.30820	7.59587	7.88354
451	1455	-0.10324	0.10194	-0.00141	-0.30074	0.29396	1.08497	-0.85023	-1.35929	-1.87029	-2.38129	-2.88247	-3.33554	-3.74614	-4.11729	4.45445	4.92084	5.33441	5.72644	6.10802	6.41569	6.70336	6.99103	7.27870	7.56637	7.85404
460	1487	-0.10364	0.11204	0.00361	-0.25115	0.39517	1.08649	-0.79053	-1.28960	-1.80060	-2.31160	-2.81274	-3.26584	-3.67644	-4.04759	4.42495	4.89134	5.29491	5.68694	6.06852	6.37619	6.66386	6.95153	7.23920	7.52687	7.81454
469	1519	-0.10404	0.12214	0.01371	-0.20156	0.49639	1.08801	-0.73067	-1.23981	-1.75081	-2.26181	-2.76294	-3.21604	-3.62664	-4.00779	4.39495	4.86134	5.26491	5.65694	6.03852	6.34619	6.63386	6.92153	7.20920	7.49687	7.78454
478	1551	-0.10444	0.13224	0.02381	-0.15197	0.59761	1.08953	-0.67073	-1.18992	-1.70092	-2.21192	-2.71304	-3.16614	-3.57674	-3.94789	4.36495	4.83134	5.23491	5.62694	6.00852	6.31619	6.60386	6.89153	7.17920	7.46687	7.75454
487	1583	-0.10484	0.14234	0.03391	-0.10238	0.69883	1.09105	-0.61085	-1.14012	-1.65112	-2.16212	-2.66324	-3.11634	-3.52694	-3.89809	4.33495	4.80134	5.20491	5.59694	5.97852	6.28619	6.57386	6.86153	7.14920	7.43687	7.72454
496	1615	-0.10524	0.15244	0.04401	-0.05279	0.79995	1.09257	-0.55095	-1.09029	-1.60129	-2.11229	-2.61344	-3.06654	-3.47714	-3.84829	4.30495	4.77134	5.17491	5.56694	5.94852	6.25619	6.54386	6.83153	7.11920	7.40687	7.69454
505	1647	-0.10564	0.16254	0.05411	-0.00320	0.90117	1.09409	-0.49105	-1.04040	-1.55140	-2.06240	-2.56354	-3.01664	-3.42724	-3.79839	4.27495	4.74134	5.14491	5.53694	5.91852	6.22619	6.51386	6.80153	7.08920	7.37687	7.66454
514	1679	-0.10604	0.17264	0.06421	0.04731	1.00239	1.09561	-0.43115	-0.99071	-1.50171	-2.01271	-2.51384	-2.96694	-3.37754	-3.74869	4.24495	4.71134	5.11491	5.50694	5.88852	6.19619	6.48386	6.77153	7.05920	7.34687	7.63454
523	1711	-0.10644	0.18274	0.07431	0.09772	1.10361	1.09713																			

```

/* ..... */
/*
 * pcmmap.c
 *
 * (C) 1997 VoCAL Technologies Ltd
 *
 * ALL RIGHTS RESERVED. PROPRIETARY AND CONFIDENTIAL
 *
 * VoCAL Technologies Ltd
 * 3032 Scott Blvd
 * Santa Clara, CA 95054
 *
 * Product      C
 *
 * Module:      PCM
 *
 * This file contains the PCM mapping functions.
 *
 * Revision Number: $Revision$
 * Revision Status: $State$
 * Last Modified:   $Date$
 * Identification:   $Id$
 *
 * Revision History: $Log$
 * Revision 1.0 1997/03/01 00:00:00 VD
 * Initial release of software
 */
/* ..... */

#include "standard.h"
#include "pcm.h"
#include <stdio.h>
#include <math.h>

/* ..... */

struct law_array_s {
    sint15 code;
    sint15 linear;
    sint15 other;
    sint15 deselect;
};

struct law_s {
    float tx_power_db;
    float rx_power_db;
    sint15 count;
    sint15 dnm;
    sint15 indistinguishable;
    sint15 x;
    sint31 bit_rate;
    struct law_array_s value[128];
} u_law u_law_rx;

#define LAW_SELECTED 0
#define LAW_DESELECTED_MIN 0x0001
#define LAW_DESELECTED_MAX 0x0002
#define LAW_DESELECTED_DMIN 0x0004
#define LAW_DESELECTED_AVOID 0x0008
#define LAW_DESELECTED_DUPLICATE 0x0010
#define LAW_DESELECTED_POWER 0x0020

/* ..... */

#define MAP_FRAME_SIZE 6

uint48 frame_slot_modulus[MAP_FRAME_SIZE];
uint48 total_symbols_per_frame

/* ..... */

#define USE_4D_TRELLIS

/* ..... */

void
u_law_init (struct law_s *law)
{

```

B1


```

sint15 idx, pcm;

law->tx_power_db = 0 0;
law->rx_power_db = 0 0;
law->count = 0;
law->indistinguishable = 0;
law->dmin = 0;
law->bit_rate = 0L;

for (idx = 0, idx < 128, ++idx) {
    pcm = 255 - idx;

    law->value[idx].code = pcm;
    law->value[idx].linear = u_law_pcm_decode (pcm);
    law->value[idx].other = u_law_pcm_threshold (pcm);
    law->value[idx].deselect = LAW_SELECTED;
}

/* ..... */

#define SELECT_LARGER /* appears to work better with standard 3 and 6 dB attenuation */

void
u_law_attenuate (struct law_s *law, float attn_db)
{
    sint15 idx, pcm;
    float attn;

    attn = db_to_float (-attn_db);

    law->tx_power_db = 0 0;
    law->rx_power_db = 0 0;
    law->count = 0;
    law->indistinguishable = 0;
    law->dmin = 0;
    law->bit_rate = 0L;

    for (idx = 0, idx < 128, ++idx) {
        pcm = 255 - idx;

        law->value[idx].other = (sint15) ((float) (u_law_pcm_decode (pcm)) * attn);
        law->value[idx].code = u_law_pcm_encode (law->value[idx].other);
        law->value[idx].linear = u_law_pcm_decode (law->value[idx].code);
        law->value[idx].deselect = LAW_SELECTED;
        if (idx != 0) {
            if (law->value[idx].code == law->value[idx-1].code) {
                law->value[idx-1].deselect = LAW_DESELECTED_DUPLICATE;
            }
            law->value[idx].deselect = LAW_DESELECTED_DUPLICATE;
        }
    }
}

/* ..... */

void
u_law_range (struct law_s *law, sint15 min, sint15 max)
{
    sint15 idx;

    for (idx = 0, idx < 128, ++idx) {
        if (law->value[idx].linear < min) {
            law->value[idx].deselect |= LAW_DESELECTED_MIN;
        }

        if (law->value[idx].linear > max) {
            law->value[idx].deselect |= LAW_DESELECTED_MAX;
        }
    }
}

/* ..... */

void
u_law_dmin (struct law_s *law, sint15 dmin)

```

B2

```

{
    sint15 idx, pcm;
    sint15 current;

    current = law->value[125].linear;
    law->value[127].deselect |= LAW_DESELECTED_AVOID;
    law->value[126].deselect |= LAW_DESELECTED_AVOID;

    for (idx = 124; idx >= 0; --idx) {
        if (law->value[idx].linear > (current - dmin)) {
            law->value[idx].deselect |= LAW_DESELECTED_DMIN;
        }
        else {
            current = law->value[idx].linear;
        }
    }
}

/* ..... */

void
u_law_discard_indistinguishable (struct law_s *law)
{
    sint15 idx;

    for (idx = 1; idx < 125; ++idx) {
        if (law->value[idx].code == law->value[idx-1].code) {
            law->value[idx-1].deselect |= LAW_DESELECTED_DUPLICATE;
        }
        else {
            law->value[idx].deselect |= LAW_DESELECTED_DUPLICATE;
        }
        if (law->value[idx-1].deselect & (LAW_DESELECTED_DMIN |
            LAW_DESELECTED_AVOID | LAW_DESELECTED_POWER)) {
            law->value[idx-1].deselect |= LAW_DESELECTED_DUPLICATE;
        }
        else {
            law->value[idx].deselect |= LAW_DESELECTED_DUPLICATE;
        }
    }
}

/* ..... */

void
u_law_attenuate_dmin (struct law_s *tx_law, struct law_s *rx_law)
{
    sint15 idx;

    rx_law->value[127].deselect |= LAW_DESELECTED_AVOID;
    rx_law->value[126].deselect |= LAW_DESELECTED_AVOID;

    for (idx = 124; idx >= 0; --idx) {
        if (tx_law->value[idx].deselect & LAW_DESELECTED_DMIN) {
            rx_law->value[idx].deselect |= LAW_DESELECTED_DMIN;
        }
    }
}

/* ..... */

void
u_law_exclude (struct law_s *law)
{
    sint15 idx, pcm;

    for (idx = 127; idx >= 0; --idx) {
        pcm = 255 - idx;

        if ((pcm == 165) || (pcm == 169)) {
            law->value[idx].deselect |= LAW_DESELECTED_AVOID;
        }
    }
}

/* ..... */

float
u_law_power (struct law_s *law, float max_db)

```

B3

```

{
    sint15 idx, count, dmin, prev;
    float factor, power, max_float;
    float tx_power, tx_sum, rx_power, rx_sum;

    factor = pow (10.0, ((3.17 + 3.01244) / 20.0)) / 8159.0;

    count = 0;
    tx_sum = 0.0;
    rx_sum = 0.0;
    dmin = 8159;
    prev = -8159;

    max_float = db_to_power (max_db);
    for (idx = 0; idx < 128; ++idx) {
        if (law->value[idx].deselect == 0) {
            rx_power = law->value[idx].linear * factor;
            rx_power = rx_power * rx_power;
            rx_sum = rx_power + rx_sum;

            tx_power = u_law.value[idx].linear * factor;
            tx_power = tx_power * tx_power;
            tx_sum = tx_power + tx_sum;

            power = tx_power / (float) (count + 1);
            if (power <= max_float) {
                rx_sum = rx_power;
                tx_sum = tx_power;
                count++;
                if ((law->value[idx].linear - prev) < dmin) {
                    dmin = law->value[idx].linear - prev;
                }
                prev = law->value[idx].linear;
            }
            else {
                law->value[idx].deselect = LAW_DESELECTED_POWER;
            }
        }
    }

    //printf ("%f %f %d %d\n", power, tx_sum, count, law->value[idx].deselect);
    tx_power = tx_sum / (float) count;
    tx_power = power_to_db (tx_power);

    rx_power = rx_sum / (float) count;
    rx_power = power_to_db (rx_power);

    law->tx_power_db = tx_power;
    law->rx_power_db = rx_power;
    law->count = count;
    law->dmin = dmin;

    return power;
}

/* ..... */

void
u_law_count_indistinguishable (struct law_s *law)
{
    sint15 idx, count;

    count = 0;
    for (idx = 1; idx < 128; ++idx) {
        if (law->value[idx].deselect == LAW_DESELECTED_DUPLICATE) {
            count++;
        }
    }
    law->indistinguishable = count;
}

/* ..... */

sint31
u_law_bit_rate (struct law_s *law)
{
    float bit_rate_float;

    bit_rate_float = (log10 ((float) law->count * 2.0) / log10(2.0)) * 8000.0;
    law->bit_rate = (sint31) bit_rate_float;
}

```

B4

```

    return law->bit_rate;
}

/* ..... */

#define MAX_SHIFT 20 /* covers to -7.08 dB */
#define MAX_SHIFT 30 /* covers to -11.2 dB */
#define MAX_SHIFT 40 /* covers to -14.65 dB */

float
u_law_detect_attenuation (struct law_s *law)
{
    sint15 idx, idx1, idx2, idx3, trim;
    sint15 count;
    float attn_low[MAX_SHIFT], attn_high[MAX_SHIFT];
    float a_low[MAX_SHIFT], a_high[MAX_SHIFT];
    float attn_diff;

    count = 0;
    idx3 = 0;

    for (idx = 128; idx >= MAX_SHIFT; --idx) {
        if (law->value[idx].deselect & LAW_DESELECTED_DUPLICATE) {
            idx3++;
            if (count == 0) {
                for (count = 0; count < MAX_SHIFT; ++count) {
#ifdef SELECT_LARGER
                    u_law.value[idx+1].linear;
                    u_law.value[idx].linear;
                    #else
                    u_law.value[idx].linear;
                    u_law.value[idx-1].linear;
                    #endif
                    //
                    attn_high[count], attn_low[count]);
                    count = MAX_SHIFT;
                }
            }
            else {
                for (idx1 = 0; idx1 < MAX_SHIFT; ++idx1) {
#ifdef SELECT_LARGER
                    u_law.value[idx+1].linear;
                    u_law.value[idx].linear;
                    #else
                    u_law.value[idx].linear;
                    u_law.value[idx-1].linear;
                    #endif
                    //
                    a_high[idx1], a_low[idx1]);
                }
                for (idx1 = 0; idx1 < count; ++idx1) {
                    trim = 1;
                    for (idx2 = 0; idx2 < MAX_SHIFT; ++idx2) {
                        if ((attn_high[idx1] >= a_high[idx2]) && (attn_low[idx1] <=
//
a_high[idx2])) {
                            printf ("reduce high %f %f %f\n",
                                attn_high[idx1], attn_low[idx1], a_high[idx2]);
                            attn_high[idx1] = a_high[idx2];
                            trim = 0;
                        }
                        if ((attn_high[idx1] >= a_low[idx2]) && (attn_low[idx1] <=
//
a_low[idx2])) {
                            printf ("increase low %f %f %f\n",
                                attn_high[idx1], attn_low[idx1], a_low[idx2]);
                            attn_low[idx1] = a_low[idx2];
                            trim = 0;
                        }
                    }
                }
            }
        }
    }
}

```

B5

```

a_low[idx2])) {
//
attn_low[idx1]).

        if ((attn_high[idx1] <= a_high[idx2]) && (attn_low[idx1] -
            printf("hold %f %f\n", attn_high[idx1],
                trim = 0;
            }
        }
        if (attn_high[idx1] < attn_low[idx1]) {
            trim = 1;
        }
        if (trim) {
            printf("trim %f %f\n", attn_high[idx1], attn_low[idx1]);
            for (idx2 = idx1; idx2 < (count - 1); ++idx2) {
                attn_high[idx2] = attn_high[idx2+1];
                attn_low[idx2] = attn_low[idx2+1];
            }
            --count;
            --idx1;
        }
    }
    if (count <= 0) {
        printf("count break\n");
        break;
    }
    if (idx3 >= 10) break;
}
if (count > 1) {
    attn = (attn_high[0] + attn_low[0]) / 2.0;
    diff = attn_high[0] - attn_low[0];
    for (idx1 = 1; idx1 < count; ++idx1) {
        if ((attn_high[idx1] - attn_low[idx1]) < diff) {
            attn = (attn_high[idx1] + attn_low[idx1]) / 2.0;
            diff = attn_high[idx1] - attn_low[idx1];
        }
    }
    printf("Multiple potential attenuations detected, resolve by generating and matching\n"
        "duplicated codes to those observed. Currently choosing largest\n"
        "range.\n");
} else {
    attn = (attn_high[0] + attn_low[0]) / 2.0;
}
attn = log10(attn) * 20.0;

//
printf("count %d attempts %d range %f %f\n", count, idx3, attn_high[0], attn_low[0]);
//
printf("attenuation detected %f\n", attn);
return attn;
}
/.....*/

uint15
u_law_map_symbol_set(struct law_s *tx_law, struct law_s *rx_law)
{
    sint15 idx; count limit;
    uint16 mask;

    total_symbols_per_frame lsw = 1;
    total_symbols_per_frame mid = 0;
    total_symbols_per_frame msw = 0;

//
printf("%04x %04x %04x\n", total_symbols_per_frame msw,
//
    total_symbols_per_frame mid, total_symbols_per_frame lsw);

    for (idx = 0; idx < MAP_FRAME_SIZE; ++idx) {
        frame_slot_modulus[idx] lsw = total_symbols_per_frame lsw;
        frame_slot_modulus[idx] mid = total_symbols_per_frame mid;
        frame_slot_modulus[idx] msw = total_symbols_per_frame msw;
    }

#ifdef USE_4D_TRELLIS
    limit = tx_law->count;
    if (idx & 1) {
        limit = limit >> 1;
    }
}

```

B6

```

        for (count = 1, count < limit; ++count) {
            uint48_add (&total_symbols_per_frame, &frame_slot_modulus[idx],
                        &total_symbols_per_frame);
        }
    #else
        for (count = 1, count < tx_law->count; ++count) {
            uint48_add (&total_symbols_per_frame, &frame_slot_modulus[idx],
                        &total_symbols_per_frame);
        }
    #endif
    //      printf("%04x %04x %04x\n" total_symbols_per_frame msw,
    //             total_symbols_per_frame mid total_symbols_per_frame lsw);
}

count = 47;
mask = 0x8000;
for (idx = 0, idx < 16; ++idx) {
    if (mask & total_symbols_per_frame msw) {
        return count;
    }
    mask = mask >> 1;
    --count;
}

mask = 0x8000;
for (idx = 0, idx < 16; ++idx) {
    if (mask & total_symbols_per_frame mid) {
        return count;
    }
    mask = mask >> 1;
    --count;
}

mask = 0x8000;
for (idx = 0, idx < 16; ++idx) {
    if (mask & total_symbols_per_frame lsw) {
        return count;
    }
    mask = mask >> 1;
    --count;
}
return count;
}

```

```

void
print_deselect (uint15 deselect)
{
    if (deselect & LAW_DESELECTED_MIN) {
        printf ("(Below Min) ");
    }

    if (deselect & LAW_DESELECTED_MAX) {
        printf ("(Above Max) ");
    }

    if (deselect & LAW_DESELECTED_AVOID) {
        printf ("(Avoid Dmin) ");
    }

    if (deselect & LAW_DESELECTED_DMIN) {
        printf ("(Between Dmin) ");
    }

    if (deselect & LAW_DESELECTED_DUPLICATE) {
        printf ("(Duplicated Code) ");
    }

    if (deselect & LAW_DESELECTED_POWER) {
        printf ("(Power Limit) ");
    }

    printf("\n");
}

```

B7

```

#define DO_FEW
/* ..... */

#define DO_PRINT_0
#define DO_PRINT_1
#define DO_PRINT_2
#define DO_PRINT_3
#define DO_PRINT_4
#define DO_PRINT_5
/* ..... */

#ifdef DO_FEW
#define MAX_ATTN 1
#define MAX_DMIN 4

#define START_DMIN 48
#define STEP_DMIN 4

#define START_ATTN 11.0
#define STEP_ATTN 1.0
/* ..... */

#else /* DO_FEW */
#define MAX_ATTN 14
#define MAX_DMIN 36

#define START_DMIN 4
#define STEP_DMIN 4

#define START_ATTN 0.0
#define STEP_ATTN 1.0
#endif /* DO_FEW */
/* ..... */

void
main (void)
{
    sint15 idx, count;
    float attn;
    sint15 bits_per_frame;
    sint31 bit_rate, overall_bit_rate;

    float input_attn;
    sint15 input_tx_dmin, input_rx_dmin;

    sint15 i, j, results_idx;

    struct results_s {
        float attn;
        sint15 dmin;
        sint31 bit_rate_simple;
        sint31 bit_rate_exclude;
        sint31 bit_rate_distinguishable_tx_dmin;
        sint31 bit_rate_distinguishable_rx_dmin;
    } results [MAX_ATTN * MAX_DMIN];

    results_idx = 0;

    input_attn = START_ATTN;
    // input_tx_dmin = 120;
    // input_rx_dmin = 120;

    for (i = 0; i < MAX_ATTN; input_attn += STEP_ATTN, i++) {
        input_tx_dmin = START_DMIN;
        input_rx_dmin = START_DMIN;

        for (j = 0; j < MAX_DMIN; input_tx_dmin += STEP_DMIN, input_rx_dmin += STEP_DMIN, j++) {
            printf ("n");
            u_law_init (&u_law);

            // u_law_range (&u_law, 30, 4000);
            // u_law_dmin (&u_law, input_tx_dmin);
            // u_law_power (&u_law, -12.0 / (-9.47981));
            // u_law_power (&u_law, -12.0);

```

B8

```

    u_law_bit_rate (&u_law).

    printf ("%6 2f %3d %3d ", input_attn, input_tx_dmin, input_rx_dmin);

//    printf ("tx power %3 2f rx power %3.2f count %d dmin %d dup %d bit rate %ld\n",
    printf ("tx pwr %3 2f rx pwr %3.2f cnt %2d dmin %3d dup %2d rate %ld\n",
        u_law.tx_power_db, u_law.rx_power_db, u_law.count, u_law.dmin,
        u_law.indistinguishable, u_law.bit_rate);

#ifdef DO_PRINT_0
    for (idx = 0; idx < 128; ++idx) {
        printf ("%3d %5d %5d %5d %5d ", u_law.value[idx].code, u_law.value[idx].linear,
            u_law.value[idx].other, u_law.pcm_encode(u_law.value[idx].linear),
            u_law.pcm_encode(u_law.value[idx].other - 1));
        print_deselect(u_law.value[idx].deselect);
    }
#endif

/* ..... */

    u_law_attenuate (&u_law_rx, input_attn);
//    u_law_range (&u_law_rx, 22, 4000);
//    u_law_dmin (&u_law_rx, input_rx_dmin);
    u_law_attenuate_dmin (&u_law, &u_law_rx) /* transfer from transmitter */
//    u_law_exclude (&u_law_rx);
//    u_law_discard_indistinguishable (&u_law_rx);
    u_law_power (&u_law_rx, -12.0);
    u_law_discard_indistinguishable (&u_law_rx);
    u_law_count_indistinguishable (&u_law_rx);
    u_law_bit_rate (&u_law_rx);

    printf ("%6 2f %3d %3d ", input_attn, input_tx_dmin, input_rx_dmin);

//    printf ("tx power %3 2f rx power %3.2f count %d dmin %d dup %d bit rate %ld\n",
    printf ("tx pwr %3 2f rx pwr %3.2f cnt %2d dmin %3d dup %2d rate %ld\n",
        u_law_rx.tx_power_db, u_law_rx.rx_power_db, u_law_rx.count,
        u_law_rx.dmin, u_law_rx.indistinguishable, u_law_rx.bit_rate);

#ifdef DO_PRINT_1
    for (idx = 0; idx < 128; ++idx) {
        printf ("%3d %5d %5d %5d ", u_law.value[idx].code, u_law_rx.value[idx].other,
            u_law_rx.value[idx].linear, u_law_rx.value[idx].code);
        print_deselect(u_law_rx.value[idx].deselect);
    }

    attn = u_law_detect_attenuation (&u_law_rx);
    printf ("attenuation detected %f\n", attn);
#endif

    results[results_idx].attn = input_attn;
    results[results_idx].dmin = input_tx_dmin;
    if (u_law_rx.dmin == 0) {
        results[results_idx].bit_rate_simple = 0;
    }
    else {
        results[results_idx].bit_rate_simple = u_law_rx.bit_rate;
    }

/* ..... */

    u_law_attenuate (&u_law_rx, input_attn);
//    u_law_range (&u_law_rx, 22, 4000);
//    u_law_dmin (&u_law_rx, input_rx_dmin);
    u_law_attenuate_dmin (&u_law, &u_law_rx) /* transfer from transmitter */
//    u_law_exclude (&u_law_rx);
//    u_law_discard_indistinguishable (&u_law_rx);
    u_law_power (&u_law_rx, -12.0);
    u_law_discard_indistinguishable (&u_law_rx);
    u_law_count_indistinguishable (&u_law_rx);
    u_law_bit_rate (&u_law_rx);

    printf ("%6 2f %3d %3d ", input_attn, input_tx_dmin, input_rx_dmin);

//    printf ("tx power %3 2f rx power %3.2f count %d dmin %d dup %d bit rate %ld\n",
    printf ("tx pwr %3 2f rx pwr %3.2f cnt %2d dmin %3d dup %2d rate %ld\n",
        u_law_rx.tx_power_db, u_law_rx.rx_power_db, u_law_rx.count,
        u_law_rx.dmin, u_law_rx.indistinguishable, u_law_rx.bit_rate);

#ifdef DO_PRINT_2

```

B9


```

for (idx = 0; idx < 128; ++idx) {
    printf ("%3d %5d %5d %5d ", u_law_value[idx].code, u_law_rx.value[idx].other,
        u_law_rx.value[idx].linear, u_law_rx.value[idx].code);
    print_deselect(u_law_rx.value[idx].deselect);
}

attn = u_law_detect_attenuation (&u_law_rx);
printf ("attenuation detected %f\n", attn);
#endif

if (u_law_rx.dmin == 0) {
    results[results_idx].bit_rate_exclude = 0;
}
else {
    results[results_idx].bit_rate_exclude = u_law_rx.bit_rate;
}

.....

u_law_attenuate (&u_law_rx, input_attn);
// u_law_range (&u_law_rx, 22, 4000);
// u_law_dmin (&u_law_rx, input_rx_dmin);
u_law_attenuate_dmin (&u_law, &u_law_rx);
u_law_discard_indistinguishable (&u_law_rx);
u_law_power (&u_law_rx, -12.0);
// u_law_power (&u_law_rx, (-12.0 - attn));
// u_law_count_indistinguishable (&u_law_rx);
u_law_bit_rate (&u_law_rx);

printf ("%6.2f %3d %3d ", input_attn, input_tx_dmin, input_rx_dmin);

// printf ("tx power %3.2f rx power %3.2f count %d dmin %d dup %d bit rate %ld\n",
printf ("tx pwr %3.2f rx pwr %3.2f cnt %2d dmin %3d dup %2d rate %ld\n",
    u_law_rx.tx_power_db, u_law_rx.rx_power_db, u_law_rx.count,
    u_law_rx.dmin, u_law_rx.indistinguishable, u_law_rx.bit_rate);

#ifdef DO_PRINT_3
for (idx = 0; idx < 128; ++idx) {
    printf ("%3d %5d %5d %5d ", u_law_value[idx].code, u_law_rx.value[idx].other,
        u_law_rx.value[idx].linear, u_law_rx.value[idx].code);
    print_deselect(u_law_rx.value[idx].deselect);
}

attn = u_law_detect_attenuation (&u_law_rx);
printf ("attenuation detected %f\n", attn);
#endif

results[results_idx].bit_rate_distinguishable_tx_dmin = u_law_rx.bit_rate;

.....

u_law_attenuate (&u_law_rx, input_attn);
// u_law_range (&u_law_rx, 22, 4000);
// u_law_dmin (&u_law_rx, input_rx_dmin);
// u_law_attenuate_dmin (&u_law, &u_law_rx);
u_law_discard_indistinguishable (&u_law_rx);
u_law_power (&u_law_rx, -12.0);
// u_law_power (&u_law_rx, (-12.0 - attn));
// u_law_count_indistinguishable (&u_law_rx);
u_law_bit_rate (&u_law_rx);

printf ("%6.2f %3d %3d ", input_attn, input_tx_dmin, input_rx_dmin);

// printf ("tx power %3.2f rx power %3.2f count %d dmin %d dup %d bit rate %ld\n",
printf ("tx pwr %3.2f rx pwr %3.2f cnt %2d dmin %3d dup %2d rate %ld\n",
    u_law_rx.tx_power_db, u_law_rx.rx_power_db, u_law_rx.count,
    u_law_rx.dmin, u_law_rx.indistinguishable, u_law_rx.bit_rate);

#ifdef DO_PRINT_4
for (idx = 0; idx < 128; ++idx) {
    printf ("%3d %5d %5d %5d ", u_law_value[idx].code, u_law_rx.value[idx].other,
        u_law_rx.value[idx].linear, u_law_rx.value[idx].code);
    print_deselect(u_law_rx.value[idx].deselect);
}

attn = u_law_detect_attenuation (&u_law_rx);
printf ("attenuation detected %f\n", attn);
#endif

```

B10

```

        results[results_idx++] bit_rate_distinguishable_rx_dmin = u_law_rx.bit_rate;
    /* ..... */

    bits_per_frame = u_law_map_symbol_set (&u_law_rx, &u_law_rx);
    bit_rate = (sint31) (((float) (bits_per_frame) / 6.0 + 1.0) * 8000.0);

#ifdef USE_4D_TRELLIS
    overall_bit_rate = (sint31) (((float) (bits_per_frame) / 6.0 + 1.0 + 0.5) * 8000.0);
#else
    overall_bit_rate = (sint31) (((float) (bits_per_frame) / 6.0 + 1.0) * 8000.0);
#endif

#ifdef DO_PRINT_5
    printf ("bits per frame %d bit rate %d overall bit rate %d (with trellis)\n", bits_per_frame,
           bit_rate, overall_bit_rate);
#endif
/* ..... */

    if 0
        for (count = 0; count < 1000; count = count + bits_per_frame) {
            generate_bits (bits_per_frame);
            u_law_send_frame (&u_law, &u_law_rx);
            u_law_receive_frame (&u_law, &u_law_rx);
            check_bits (bits_per_frame);
        }
    #endif
/* ..... */
}
/* ..... */

#ifdef DO_FEW
    for (idx = 0; idx < MAX_ATTN * MAX_DMIN; idx++) {
        printf ("%6d %3d %5ld %5ld %5ld %5ld\n", results[idx].attn, results[idx].dmin,
               results[idx].bit_rate_simple, results[idx].bit_rate_exclude,
               results[idx].bit_rate_distinguishable_tx_dmin,
               results[idx].bit_rate_distinguishable_rx_dmin);
    }
#endif
}
/* ..... */

```

B11

```

/* ..... */
/*
 * pcmcnv.c
 *
 * (C) 1997 VoCAL Technologies Ltd.
 *
 * ALL RIGHTS RESERVED. PROPRIETARY AND CONFIDENTIAL.
 *
 * VoCAL Technologies Ltd.
 * 3032 Scott Blvd
 * Santa Clara, CA 95054
 *
 * Product:      C
 *
 * Module:       PCM
 *
 * This file contains the PCM conversion functions.
 *
 * Revision Number:    $Revision$
 * Revision Status:    $State$
 * Last Modified:      $Date$
 * Identification:     $Id$
 *
 * Revision History:    $Log$
 * Revision 1.0 1997/03/01 00:00:00 VD
 * Initial release of software
 */
/* ..... */

#include "standard.h"
#include "pcm.h"
/* ..... */

#include <stdio.h>

sint15
u_law_pcm_encode (sfract15 input)
{
    sfract15 value, seg;

    value = input;
    if (input < 0) value = -input;          /* Take absolute value */

    value = value + 33;
    if (value > 8159) value = 8159;        /* Limit values */

    seg = iexp (value);                    /* Compute exponent */
    //printf("%5d %5d %5d", input, value, seg);
    value = norm (value, seg);             /* Normalize value */

    value = value ^ 0x4000;                /* Clear bit */
    value = value >> 10;                  /* Position bits */
    //printf(" %5d", value);

    if (input < 0) {
        value = value | 0x0080;           /* Insert sign bit */
    }

    seg = seg + 9;
    seg = seg << 4;                       /* Compute segment */

    value = value | seg;                  /* Insert segment bits */
    //printf(" %04x", value);

    value = value ^ 0x00ff;               /* Invert bits */
    //printf(" %5d\n", value);
    return (sint15) value;
}

#ifdef DO_U_LAW
x
x
x      AR = ABS AR;                      /* Input sample passed in AR (1,15) */
x      AY0 = 132;                        /* Take absolute value */
x      AR = AR + AY0;                    /* 33 << 2 */
x      SR1 = 32636;                      /* Limit values */
x      IF AV AR = PASS SR1;
x      SE = EXP AR (HI);                 /* Compute exponent */
x

```

B12

```

x          SR = NORM AR (LO);          /* Normalize value */
x          AY0 = 0x4000;
x          AR = SR0 XOR AY0;            /* Clear bit */
x          SR = LSHIFT AR BY -10 (LO);  /* Position bits */
x          AX0 = SF, AR = PASS AY0;
x          IF POS AR = PASS 0;          /* Create sign bit */
x          SR = SR OR LSHIFT AR BY -7 (LO); /* Insert sign bit */
x          AY0 = 7;                    /* 9 if using 8031 range */
x          AR = AX0 + AY0;              /* Compute segment */
x          SR = SR OR LSHIFT AR BY 4 (LO); /* Insert segment bits */
x          AY0 = 0xFF;
x          AR = SR0 XOR AY0;            /* Invert bits */
x          RTS;                        /* Pass on rate converted value */
#endif

```

/* */

```

sfract15
u_low_pcm_decode (uint8 code)
{
    sfract15 value, seg;

    value = code & 0x00ff;              /* Mask bits */
    value = value ^ 0x00ff;              /* Invert bits */

    seg = value & 0x0070;                /* Isolate segment bits */
    value = value ^ seg;                  /* Remove segment bits */
    seg = seg >> 4;                      /* Shift to low bits */

    if ((value - 0x0080) >= 0) {          /* Determine sign */
        value = value + 0xff80;           /* Process negative value */
        value = value + value + 33;       /* Add segment offset */
        value = value << seg;             /* Position bits */
        value = 33 - value;               /* Remove segment offset */
    }
    else {
        value = value + value + 33;        /* Add segment offset */
        value = value << seg;              /* Position bits */
        value = value - 33;                /* Remove segment offset */
    }

    return value;
}

```

/* */

```

sfract15
u_low_pcm_threshold (uint8 code)
{
    sfract15 value, seg;

    value = code & 0x00ff;              /* Mask bits */
    value = value ^ 0x00ff;              /* Invert bits */

    seg = value & 0x0070;                /* Isolate segment bits */
    value = value & 0x000f;               /* Remove segment bits */
    seg = seg >> 4;                      /* Shift to low bits */
    seg++;

    value = value + 17;                   /* Add segment offset */
    value = value << seg;                 /* Position bits */
    value = value - 33;                   /* Remove segment offset */

    if ((code & 0x80) == 0) {             /* Determine sign */
        value = -value;                   /* Process negative value */
    }

    return value;
}

```

/* */

#ifdef DO_A_LAW

```

a_low_pcm_encode          /* Input sample passed in AR (1.15) */
                          /* Take absolute value */
    AR = ABS AR;          /* Check for zero segment */
    AY0 = 511;            /* 127 */
    AF = AR - AY0;
    IF GT JUMP a_low_pcm_enc_1;

```

B13

```

SR = LSHIFT AR BY -4 (LO); /* Downshift bits */
AR = 0x4000;
IF NEG AR = PASS 0; /* Create sign bit */
SR = SR OR LSHIFT AR BY -7 (LO); /* Insert sign bit */
AY0 = 0x55;
AR = SR0 XOR AY0; /* Invert bits */
RTS; /* Pass on rate converted value */

a_low_pcm_enc_1
SE = EXP AR (HI); /* Compute exponent */
AX0 = SE, SR = NORM AR (LO); /* Normalize value */
AY0 = 0x4000;
AR = SR0 XOR AY0; /* Clear bit */
SR = LSHIFT AR BY -10 (LO); /* Position bits */
AR = PASS AY0;
IF NEG AR = PASS 0; /* Create sign bit */
SR = SR OR LSHIFT AR BY -7 (LO); /* Insert sign bit */
AY0 = 7;
AR = AX0 + AY0; /* Compute segment */
IF ! ! AR = PASS 0;
SR = SR OR LSHIFT AR BY 4 (LO); /* Insert segment bits */
AY0 = 0x55;
AR = SR0 XOR AY0; /* Invert bits */
RTS; /* Pass on rate converted value */

ident(IDENT, RX, B1, PCM_DECODE);

a_low_pcm_decode /* Input sample passed in AR */
AY0 = 0x55; /* Mask bits for inversion */
AR = AR XOR AY0; /* Invert bits */
SR1 = 0x3; /* Set sign bit */
SR0 = 0x800; /* Set LSB of interval */
SR = SR OR LSHIFT AR BY -12 (LO); /* Isolate segment and interval */
AY0 = 32;
AX0 = AR, AF = PASS AY0;
AY0 = 9; /* Segment bias */
AR = SR1 - AY0; /* Determine shift */
IF LT AF = PASS 0; /* No extra MSB bit */
IF EQ AR = PASS 0; /* No less than zero bits */
SR = LSHIFT SR0 BY -11 (LO); /* Isolate interval */
SE = AR, AR = SR0 OR AF; /* Add bit if necessary */
SR = LSHIFT AR (LO); /* Position output */
SR = LSHIFT SR0 BY 3 (LO);
AY0 = 0xFF80;
AR = SR0, AF = AX0 + AY0; /* Check if sign bit set */
IF LT AR = - SR0; /* If it is, negate result */
RTS; /* Pass on rate converted value (1 15) */

#endif /* DO_A_LAW */

```

B14

```

/* ..... */
/*
 * math.c
 *
 * (C) 1997 VoCAL Technologies Ltd.
 *
 * ALL RIGHTS RESERVED PROPRIETARY AND CONFIDENTIAL
 *
 * VoCAL Technologies Ltd
 * 3032 Scott Blvd
 * Santa Clara, CA 95054
 *
 * Product      C
 * Module       MATH
 *
 * This file contains fractional math support functions
 *
 * Revision Number   $Revision$
 * Revision Status   $State$
 * Last Modified    $Date$
 * Identification    $Id$
 *
 * Revision History:   $Log$
 * Revision 1.0 1997/03/01 00:00:00 VD
 * Initial release of software
 */
/* ..... */

```

```

#include "standard.h"
#include "pcm.h"
#include <math.h>
/* ..... */

```

```

sint15
iexp (sfract15 value)
{
    sint15 exp;

    if (value < 0) {
        value = -value;
    }

    exp = 15;

    if (value == 0) {
        return exp;
    }

    exp = 0;
    while ((value & 0x4000) == 0) {
        --exp;
        value = value << 1;
    }

    return exp;
}
/* ..... */

```

```

sint15
norm (sfract15 value, sint15 exp)
{
    return (value << -exp);
}
/* ..... */

```

```

float
db_to_float (float db)
{
    float db_float;

    db_float = db / 20.0;
    db_float = pow (10.0, db_float);

    return db_float;
}

```

B15

```

}
/* ..... */

float
db_to_power (float db)
{
    float db_float;

    db_float = db / 10.0;
    db_float = pow (10.0, db_float);

    return db_float;
}
/* ..... */

float
float_to_db (float power)
{
    float float_db;

    float_db = log10 (power) * 20.0;

    return float_db;
}
/* ..... */

float
power_to_db (float power)
{
    float power_db;

    power_db = log10 (power) * 10.0;

    return power_db;
}
/* ..... */

void
uint48_add (uint48 *src1, uint48 *src2, uint48 *dst)
{
    uint16 s1l, s1m, s1h, s2l, s2m, s2h, dstl, dstm, dsth;

    s1l = src1->lsw;
    s1m = src1->mid;
    s1h = src1->msw;

    s2l = src2->lsw;
    s2m = src2->mid;
    s2h = src2->msw;

    asm {
        mov ax, s1l;
        add ax, s2l;
        mov dstl, ax;

        mov ax, s1m;
        adc ax, s2m;
        mov dstm, ax;

        mov ax, s1h;
        adc ax, s2h;
        mov dsth, ax;
    }

    dst->lsw = dstl;
    dst->mid = dstm;
    dst->msw = dsth;

    // printf("%04x %04x %04x = %04x %04x %04x + %04x %04x %04x\n",
    //         dsth, dstm, dstl, s1h, s1m, s1l, s2h, s2m, s2l);
}
/* ..... */

void

```

B16

```

uint48_sub (uint48 *src1, uint48 *src2, uint48 *dst)
{
    uint16 s1l, s1m, s1h, s2l, s2m, s2h, dstl, dstm, dsth;

    s1l = src1->lsw,
    s1m = src1->mid,
    s1h = src1->msw;

    s2l = src2->lsw,
    s2m = src2->mid,
    s2h = src2->msw;

    asm {
        mov ax, s1l,
        sub ax, s2l,
        mov dstl, ax,

        mov ax, s1m,
        sub ax, s2m,
        mov dstm, ax,

        mov ax, s1h,
        sub ax, s2h,
        mov dsth, ax,
    }

    dst->lsw = dstl;
    dst->mid = dstm;
    dst->msw = dsth;
}

```

```

sfract15
fmpy (sfract15 a, sfract15 b)
{
    long a_long, b_long,
    short a_short;

    a_long = a;
    b_long = b;

    a_long = a_long * b_long;
    a_short = (short) (a_long >> 15);

    return a_short;
}

```

B17


```

/* ..... */
/*
 * pcm.h
 *
 * (C) 1997 VoCAL Technologies Ltd
 *
 * ALL RIGHTS RESERVED. PROPRIETARY AND CONFIDENTIAL.
 *
 * VoCAL Technologies Ltd
 * 3032 Scott Blvd
 * Santa Clara, CA 95054
 *
 * Product: C
 *
 * Module PCM
 *
 * This file defines the PCM utility functions
 *
 * Revision Number $Revision$
 * Revision Status $State$
 * Last Modified $Date$
 * Identification $Id$
 *
 * Revision History $Log$.
 */
/* ..... */

#ifndef PCM_PCM_H
#define PCM_PCM_H

/* ..... */

typedef struct {
    uint16 lsw;
    uint16 mid;
    uint16 msw;
} uint48;

sint15 lexp (sfract15 value);
sint15 norm (sfract15 value, sint15 exp);
float db_to_float (float db);
float db_to_power (float db);
float float_to_db (float power);
float power_to_db (float power);

void uint48_add (uint48 *src1, uint48 *src2, uint48 *dst);
void uint48_sub (uint48 *src1, uint48 *src2, uint48 *dst);

sint15 u_law_pcm_encode (sfract15 input);
sfract15 u_law_pcm_decode (uint8 code);
sfract15 u_law_pcm_threshold (uint8 code)

/* ..... */

#endif /* _PCM_PCM_H */

```

B18

```

/* ..... */
/*
 * standard h
 *
 * (C) 1994, 1995, 1996 VoCAL Technologies Ltd.
 *
 * ALL RIGHTS RESERVED. PROPRIETARY AND CONFIDENTIAL.
 *
 * VoCAL Technologies Ltd.
 * 3032 Scott Blvd
 * Santa Clara, CA 95054
 *
 * Product      MODEM 101
 *
 * Module              SYSTEM
 *
 * This file defines the standard system definitions
 *
 * Revision Number      $Revision$
 * Revision Status      $State$
 * Last Modified        $Date$
 * Identification.      $Id$
 *
 * Revision History      $Log$
 */
/* ..... */

#ifndef _SYSTEM_STANDARD_H
#define _SYSTEM_STANDARD_H

/* ..... */

#ifndef DO_CX025
#include <GLBL_Globals.h>
#include <m68EC040.h>
#endif /* DO_CX025 */

#ifndef DO_WIN
/*-#include <_null.h>-*/
#define _STDC FALSE
/*#include <stddef.h>*/

#definestrup(a) _strup(a)
#definestrlwr(a) _strlwr(a)
#defineinp(a) _inp(a)
#defineinpw(a) _inpw(a)
#defineoutp(a,b) _outp(a,b)
#defineoutpw(a,b) _outpw(a,b)

#ifndef DO_WIN32
#ifndef DO_AD12181
#define DEBLEVEL 1
#define DEBUG
#include <debug.h> /*- DDK Debug Header File -*/
/*#define _Debug_Printf_Service LCODE__Debug_Printf_Service*/
/*#include <xydwaps.h>*/
#endif /* DO_AD12181 */
#define far
#define near
#define NULL ((void *)0)
#endif /* DO_WIN32 */

#else /* DO_WIN */

#ifndef DO_CX018_A
/*-#include <_null.h>-*/
#ifndef NULL
#if defined(__TINY__) || defined(__SMALL__) || defined(__MEDIUM__)
#define NULL 0
#else
#define NULL 0L
#endif
#endif
#endif /* DO_CX018_A */

#endif /* DO_WIN */

```

B19

```

/* ..... */
typedef unsigned char uint8; /* range 0-255 */
typedef unsigned char umod8; /* 8 bit math requirements */
typedef unsigned char octet; /* octet data */
#ifdef DO_FORCED_BYTE_ALIGNED
typedef unsigned short pack8;
#else /* DO_FORCED_BYTE_ALIGNED */
typedef unsigned char pack8; /* packed octet data */
#endif /* DO_FORCED_BYTE_ALIGNED */
typedef pack8 expand8; /* expand octet data to uint16 */
typedef signed char sint7;

typedef unsigned short uint16;
typedef signed short sint15;
typedef signed short sfract15;

typedef unsigned long uint32;
typedef signed long sint31;

#ifdef DO_CX025
#define far
#define interrupt
#endif /* DO_CX025 */
/* ..... */

#define MAX_UINT8 (255)
#define MAX_SINT7 (127)
#define MIN_SINT7 (-128)

#define MAX_UINT16 (65535)
#define MAX_SINT15 (32767)
#define MIN_SINT15 (-32768)

#define MAX_UINT32 (4294967296)
#define MAX_SINT31 (2147483647)
#define MIN_SINT31 (-2147483648)

#define MIN_DOUBLE (1.7e-308)
#define MAX_DOUBLE (1.7e308)
/* ..... */

typedef uint8 byte;
typedef uint16 word;

typedef int bool;

#ifdef DO_CX025
#define FALSE 0
#define TRUE (!FALSE)
#endif /* DO_CX025 */

#ifdef DO_ADI2181 || defined(DO_ISAR)
typedef uint32 dsp_pm_t; /* Of size of DSP program memory contents */
typedef uint16 dsp_dm_t; /* Of size of DSP data memory contents */
typedef uint16 dsp_addr_t; /* Of size of DSP addresses */
typedef uint16 dsp_xddr_t; /* Of size of extended DSP addresses */
#endif /* DO_ADI2181 || DO_ISAR */
/* ..... */

#define forever for (...)

#ifdef DO_CX025
#define interrupt_disable_onto_stack() \
asm("ori w, #0x0700, sr")
#define interrupt_restore_from_stack() \
asm("andi w, #0xF8FF, sr")
#else /* DO_CX025 */
#ifdef DO_CX018_A
#define interrupt_disable_onto_stack() \
{asm("ORI #0x700, SR\n NOP\n NOP\n");}
#define interrupt_restore_from_stack() \
{asm("ANDI #0xF8ff, SR\n NOP\n NOP\n");}
#else /* DO_CX018_A */
#endif
#endif /* DO_CX025 */

#ifdef DO_WIN
#define interrupt_disable_onto_stack()

```

B20

```

#define interrupt_restore_from_stack()
#else /* DO_WIN */
#define interrupt_disable_onto_stack() {asm pushf;asm cli;}
#define interrupt_restore_from_stack() {asm popf;}
#endif /* DO_WIN */

#endif /* DO_CX018_A */
#endif /* DO_CX025 */

#ifdef DO_CAPI20
#define DEBLEVEL 1
#pragma code_seg("_LTEXT", "LCODE")
#include <debug.h>
#include <vxdwraps.h>

#else /* DO_CAPI20 */
#ifdef DO_ISAR
typedef const char far LPCSTR;
typedef char far LPSTR;
#define PASCAL pascal
#endif /* DO_ISAR */
#endif /* DO_CAPI20 */

/* ..... */

#ifdef DO_WIN32
// #define sprintf sprintf
#endif /* DO_WIN32 */

/* ..... */
/* ..... */
/* ..... */
/* ..... */

#define print_debug_off(A)
#define print_diag_off(A)

#ifdef DO_CAPI20
#define print_primary(A) print_routine A
#define print_std(A) print_routine A
#define print_info(A) print_routine A
#define print_diag_on(A) print_routine A
#define print_debug_on(A) print_routine A
#define report_anomaly(A) report_anomaly_routine(A)
#else /* DO_CAPI20 */

#define print_std(A) Debug_Printf A
#define print_info(A) Debug_Printf A
#define print_diag_on(A) Debug_Printf A
#define print_debug_on(A) Debug_Printf A
#define report_anomaly(A) report_anomaly_routine(A)

#endif /* DO_CAPI20 */

#ifdef DO_PRINTS_DISABLED
#undef print_primary
#undef print_std
#undef print_info
#undef print_debug
#undef report_anomaly
#define print_primary(A)
#define print_std(A)
#define print_info(A)
#define print_debug(A)
#define report_anomaly(A)
#endif /* DO_PRINTS_DISABLED */

#ifdef DO_CX025
#undef print_primary(A)
#undef print_std(A)
#undef print_info(A)
#undef print_debug(A)
#undef report_anomaly(A)
#endif /* DO_CX025 */

/* ..... */

#endif /* SYSTEM_STANDARD_H */

```

B21

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 0 871 303 A3

(12)

EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
27.10.1999 Bulletin 1999/43

(51) Int. Cl.⁶: **H04L 25/49**, H04L 5/14

(43) Date of publication A2:
14.10.1998 Bulletin 1998/42

(21) Application number: **98106516.2**

(22) Date of filing: **08.04.1998**

(84) Designated Contracting States:
**AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE**
Designated Extension States:
AL LT LV MK RO SI

(30) Priority: **08.04.1997 US 43066 P**

(71) Applicants:
• **Demjanenko, Victor**
Pendleton, New York 14094 (US)

• **Hirzel, Frederic J.**
Sunnyvale, California 94086 (US)

(72) Inventors:
• **Demjanenko, Victor**
Pendleton, New York 14094 (US)
• **Hirzel, Frederic J.**
Sunnyvale, California 94086 (US)

(74) Representative: **Celestino, Marco**
ABM, Agenzia Brevetti & Marchi,
Via A. Della Spina 40
56125 Pisa (IT)

(54) **Method for determining the attenuation of a PCM signal over a digital channel**

(57) A method of determining digital channel attenuation; comprising the steps of: receiving a known training sequence of PCM codes, which PCM codes are subjected to the attenuation within the digital channel; quantizing the received known training sequence of PCM codes according to a predetermined thresholding procedure; identifying identical PCM codes created as a result of the thresholding procedure; and, determining the attenuation of the digital channel based upon the identification of identical PCM codes. A method is also disclosed for determining a digital channel PCM code transformation comprising receiving a known training sequence of PCM codes, which PCM codes are subjected to the PCM code transformation within the digital channel, quantizing the received known training sequence of PCM codes according to a predetermined thresholding procedure, and determining the transformation of transmitted codes to those received. A method is also disclosed for improved echo cancellation in a communications network having an analog and a digital modem, comprising saving codes transmitted from the digital modem to the analog modem for echo cancellation, transforming, by a mapping table, codes transmitted from said digital modem to codes received by the analog modem, and, using the received codes as a reference signal for cancellation of echo. A method of improved spectral shaping using a transmit shaping transfer function in a communications network having

an analog and a digital modem, comprising, transforming, by a mapping table, codes transmitted from the digital modem to codes received by the analog modem, using the received codes for transformation to their linear value equivalent representations, and, applying the linear value representations to the transmit shaping transfer function:

EP 0 871 303 A3



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 98 10 6516

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
A	US 5 394 437 A (DAGDEVIREN NURI R ET AL) 28 February 1995 (1995-02-28) * abstract * * column 8, line 61 - column 10, line 61 *	1-3	H04L25/49 H04L5/14
A	WO 96 18261 A (TOWNSHEND BRENT) 13 June 1996 (1996-06-13) * abstract * * page 39, line 1 - line 12 *	1-3	
A	KALET I ET AL: "THE CAPACITY OF PCM VOICEBAND CHANNELS" PROCEEDINGS OF THE INTERNATIONAL CONFERENCE ON COMMUNICATIONS (ICC), GENEVA, MAY 23 - 26, 1993, vol. 1, 23 May 1993 (1993-05-23), pages 507-511, XP000371143 IEEE, USA * page 509, left-hand column, paragraph 4 - right-hand column, paragraph 1 *	1-3	
P,X	EP 0 833 481 A (TELIA AB) 1 April 1998 (1998-04-01) * the whole document *	1-3	TECHNICAL FIELDS SEARCHED (Int.Cl.6) H04L
P,X	WO 98 13979 A (MOTOROLA INC) 2 April 1998 (1998-04-02) * abstract * * page 13, line 4 - line 28 * * page 18, line 6 - page 20, line 10 * * claims 1,2 *	1-3	
-/-			
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 2 September 1999	Examiner Koukourlis, S
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			

EPO FORM 1503 (03/02) (P04031)



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 98 10 6516

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
E	US 5 825 823 A (OKUNEV YURI ET AL) 20 October 1998 (1998-10-20) * abstract * * column 3, line 54 - column 4, line 37 * * column 5, line 65 - column 6, line 36; figure 2 * * column 7, line 19 - line 28 *	1,3	
E	WO 98 39866 A (3COM CORP) 11 September 1998 (1998-09-11) * abstract * * page 7, line 6 - page 12, line 23 * * claims 1,13,14 * * figures 1,4 *	1,3	
			TECHNICAL FIELDS SEARCHED (Int.Cl.6)
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 2 September 1999	Examiner Koukourlis, S
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons</p> <p>& : member of the same patent family, corresponding document</p>			

EP 0 871 303 A3 (P04001)



European Patent
Office

Application Number

EP 98 10 6516

CLAIMS INCURRING FEES

The present European patent application comprised at the time of filing more than ten claims.

- ☐ Only part of the claims have been paid within the prescribed time limit. The present European search report has been drawn up for the first ten claims and for those claims for which claims fees have been paid, namely claim(s):
- ☐ No claims fees have been paid within the prescribed time limit. The present European search report has been drawn up for the first ten claims.

LACK OF UNITY OF INVENTION

The Search Division considers that the present European patent application does not comply with the requirements of unity of invention and relates to several inventions or groups of inventions, namely:

see sheet B

- ☐ All further search fees have been paid within the fixed time limit. The present European search report has been drawn up for all claims.
- ☐ As all searchable claims could be searched without effort justifying an additional fee, the Search Division did not invite payment of any additional fee.
- ☐ Only part of the further search fees have been paid within the fixed time limit. The present European search report has been drawn up for those parts of the European patent application which relate to the inventions in respect of which search fees have been paid, namely claims:
- ☒ None of the further search fees have been paid within the fixed time limit. The present European search report has been drawn up for those parts of the European patent application which relate to the invention first mentioned in the claims, namely claims:

1-3



European Patent
Office

**LACK OF UNITY OF INVENTION
SHEET B**

Application Number

EP 98 10 6516

The Search Division considers that the present European patent application does not comply with the requirements of unity of invention and relates to several inventions or groups of inventions, namely:

1. Claims: 1-3

Method of determining digital channel attenuation.

2. Claim : 4

Method of echo cancellation.

3. Claim : 5

Method of spectral shaping.

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 98 10 6516

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

02-09-1999

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 5394437 A	28-02-1995	NONE	
WO 9618261 A	13-06-1996	AU 701274 B	21-01-1999
		AU 4418496 A	26-06-1996
		AU 708085 B	29-07-1999
		AU 9422098 A	21-01-1999
		AU 708086 B	29-07-1999
		AU 9422198 A	21-01-1999
		CA 2182974 A	13-06-1996
		EP 0745302 A	04-12-1996
		JP 9512689 T	16-12-1997
		US 5801695 A	01-09-1998
		US 5835538 A	10-11-1998
		US 5859872 A	12-01-1999
		US 5809075 A	15-09-1998
EP 0833481 A	01-04-1998	NO 974242 A	30-03-1998
		SE 9603532 A	28-03-1998
WO 9813979 A	02-04-1998	AU 4736697 A	17-04-1998
		GB 2332605 A	23-06-1999
US 5825823 A	20-10-1998	NONE	
WO 9839866 A	11-09-1998	AU 6447798 A	22-09-1998
		EP 0916202 A	19-05-1999

EPO FORM P4489

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82